



freeVoice Fox FX810 DECT Cordless

The cordless DECT headset freeVoice Fox FX810 DECT makes you independent of your desk. The easy installation and intuitive operation makes it an ideal headset for both beginners as well as for more versed frequent callers.

Remote Call Control

The integrated EHS interface lets you accept and end calls on the headset. You can also adjust the volume to suit your needs and mute the microphone.

Best sound quality with no restrictions on comfort

The noise-cancelling microphone effectively filters out troublesome ambient noise. With the headband and the large soft ear pads, the headset adapts perfectly to your head and ear, thus leading to a further improvement in understanding.

Comprehensive hearing protection

The headset offers comprehensive hearing protection that has been certified in accordance with DIN EN 60950-1 to protect your ears against sudden noise peaks



Features and advantages

Headset FOX FX810M

Wearing style	Headband, designed to be worn all day.
Call control	Call acceptance key to accept, end and reject a call; docking operations can also accept and end calls.
Display signal	LED shows call status, pairing status and other events.
Audio signals	Audio signals indicate incoming calls, low battery charge, volume, muting and connection status.
Sound quality	DSP noise cancelling, echo cancellation, tone control, narrow-band audio.
Noise-cancelling microphone	Medium-length microphone with ambient noise cancelling effectively reduces background noise and improves understanding.
Charging	When docked onto the Fox FX 810 DECT base station.
Standard for wireless communication:	(CAT-1q) EU DECT.
DECT range:	Up to 100 m range from the Fox FX 810 DECT base station to the headset.
DECT frequencies	EU DECT: 1.88 – 1.90 GHz.
Audio-shock protection	Protects the user's hearing by adjusting noise peaks and sudden loud noise down to a safe level (Certificate EMC Directive 2004/108/EC Certificate No.: RXM09102151-1, RXM09102151-2).
Loudspeaker	Broadband loudspeaker.
Weight	43 grams lightweight headset.
SAR value	The output is below 20mW and thus below the minimum limit in accordance with EN62479, hence making it safe.

Headset battery

Battery type:	Lithium-ion polymer.
Charging time: Battery status LED	Shows the battery status and tells you when the battery has to be recharged. 20% charge in less than 20 minutes, 50% in less than 45 minutes, full charge in less than 3 hours.
Battery service life:	At least 1000 charging cycles.
Shelf life of the battery	Shelf life of the battery: The headset battery retains its charge for at least 6 months when it is switched off before the battery has to be recharged.
Talk time	Up to 8 hours.
Standby time:	At least 50 hours.

Base station Fox 810 DECT

Desk phone connections	RJ-11 for handset, RJ-11 for telephone (or headset socket), RJ-45 for AUX (for EHS adapter or lifter).
Compatibility	The headset can be used on all common desk phones.

Scope of delivery

DECT headset with desktop charging station, mains adapter and headband.

Article number/Warranty

FX810M

Warranty	2 years.
----------	----------



C+HC Computer + Headset Company GmbH
Die Headset Spezialisten
Borsteler Chaussee 49 | 22453 Hamburg | Tel.: (040) 500 580 20
www.comhead.de